

## METROPOOL ENSCHEDE Tech Specs Audio Leffe Stage

Please read all our info below.  
Most info covers frequently asked questions in advance sheets.  
Do feel free to use all info's below to complete your tour book!

If any given information is unclear, or you foresee a serious issue production wise,  
please contact our advancing crew as soon as possible.

We are looking forward to welcoming you at our venue.  
Be nice, respect our notes mentioned below, and let's have a wonderful show together!

See you soon at Metropool!

### METROPOOL CONTACT

#### Sound

Ronald Geerdink  
[ronald@metropool.nl](mailto:ronald@metropool.nl)  
+31(0)74 243 80 00 (Tuesday-Wednesday 10-14h)

#### Light

Timo Klein Nulent  
[Timo@metropool.nl](mailto:Timo@metropool.nl)  
+31(0)74 243 80 00 (Tuesday-Thursday 9-17h)

DJ-set (all stages):  
1x Pioneer DJM-900NXS  
1x Pioneer DJM-900NXS2  
1x Pioneer DJM-800  
1x Allen & Heath Xone92  
3x Pioneer CDJ-2000NXS  
4x Pioneer CDJ-3000  
4x Technics SL1200

Last Update: 26-09-2024

## HERTOG JAN ZAAL

**Max sound level:** 103 DBA over 15 minutes,  
DUTCH COVENANT, RESPECT THIS, THANK YOU

**Capacity:** 500 / 800  
**Stage size:** 14 x 6 meters, side stage; 2 meters, height; 1,10 meters  
**Clearance:** 6,5 meter (on stage)

**Guest Power Light:** 1x 63A CEE-form, Stage Left  
1x 32A CEE-form, Stage Left  
**Guest Power Sound:** 32A CEE-form, Both Sides  
Backline power 220V, 220 to 110 volts convertors available

**Risers:** 10 x Stage decks 2 x 1 meter decks standard.  
20cm, 40cm (with and without castors), 60cm, 80cm en 100cm legs.

### HOUSE PA SPECS

**PA; each side:** 3 x D&B AL60 Augmented Array (2 x 10", 1 x 1,4") Top  
1 x D&B AL60 (2 x 10", 1 x 1,4") Out fill  
1 x D&B 44S (2 x 4.5", 2 x 1.25") Under Balcony Fill  
2 x D&B AL90 (2 x 10", 1 x 1,4") Balcony Fill  
**Subs (total):** 8 x D&B XSL-G Sub (18"/ 12" Dispersion Cardioid)  
**Amps / processing:** 5 x D&B 40D amp

**Multicore:** LK150 based system 48 lines  
8 x AES  
6 x UTP  
4 x MAD1 (BNC)

**FOH Desk:** Digico SD5c 48/24 incl waves Super rack  
**Rack:** SD-rack 32 bit

**Monitor desk:** Digico SD12  
**Rack:** D2-Rack 48/24

**Wedges:** 10 x D&B MAX2 (15"/1,4" coaxially mounted)  
**Drumfill:** 2 x D&B MAX2 (15"/1,4" coaxially mounted)  
2 x D&B B6 Sub (18")  
**Amps/processing:** 3 x D&B D20

**Microphones:** Shure, Sennheiser, AKG, neumann etc.  
**DI's:** Klark/ Radial/ BSS

*Last Update: 26-09-2024*